

**Final Exam SCE2202**  
**System identification and optimal**  
**estimation**  
**Friday June 10, 2011 Time: kl. 9.00 -**  
**15.00**

The final exam consists of: 4 tasks.  
The exam counts 70% of the final grade.

Available aids: pen and paper

Teacher: PhD David Di Ruscio  
Systems and Control Engineering  
Department of technology  
Telemark University College  
N-3914 Porsgrunn

## Task 1 (16%): Subspace System Identification of Deterministic Systems: Using shift invariance principle

Consider the discrete time deterministic model, ie.

$$x_{k+1} = Ax_k + Bu_k, \quad (1)$$

$$y_k = Dx_k + Eu_k, \quad (2)$$

where the following output and input data matrices are known

$$Y = \begin{bmatrix} y_0^T \\ y_1^T \\ \vdots \\ y_{N-1}^T \end{bmatrix} \in \mathbb{R}^{N \times m}, \quad U = \begin{bmatrix} u_0^T \\ u_1^T \\ \vdots \\ u_{N-1}^T \end{bmatrix} \in \mathbb{R}^{N \times r}. \quad (3)$$

- a) Based on the model in Eqs. (1) and (2) and with known data as given in (3) we can develop the following matrix equation

$$Y_{0|L+1} = O_{L+1}X_0 + H_{L+1}^d U_{0|L+g}, \quad (4)$$

where  $L \geq 1$  is a user specified positive integer parameter.

Write down the structure of the matrices in the matrix Eq. (4), with parameters  $N = 9$ ,  $L = 2$  and  $g = 0$ .

- b) By using the known input-output data (3) and Eq. (4) we may formulate the projected equation

$$Z_{0|L+1} = O_{L+1}X_0^a \quad (5)$$

Find expressions for the data matrix  $Z_{0|L+1}$ .

Remark: define the projections which is involved in the expressions for  $Z_{0|L+1}$ .

- c) Show how
- the system order,  $n$
  - the extended observability matrix  $O_{L+1}$
  - the system matrices  $A$  and  $D$

can be estimated.

- d) Based on the model in Eqs. (1) and (2) and with known data as given in (3) we can develop the following matrix equation

$$Y_{1|L} = \tilde{A}_L Y_{0|L} + \tilde{B}_L U_{0|L+g}. \quad (6)$$

Give an outline of how the model matrices  $B$  and  $E$  may be estimated, by using Eq. (6) and that model matrices  $A$  and  $D$  are known from task c) above ?

## Task 2 (16%): Subspace System Identification: Combined Systems

Consider the discrete time model on innovations form, ie.

$$x_{k+1} = Ax_k + Bu_k + Ce_k, \quad (7)$$

$$y_k = Dx_k + Eu_k + Fe_k \quad (8)$$

where  $e_k$  is white noise with unit covariance matrix, i.e.,  $E(e_k e_k^T) = I$  and where the following output and input data matrices are known

$$Y = \begin{bmatrix} y_0^T \\ y_1^T \\ \vdots \\ y_{N-1}^T \end{bmatrix} \in \mathbb{R}^{N \times m}, \quad U = \begin{bmatrix} u_0^T \\ u_1^T \\ \vdots \\ u_{N-1}^T \end{bmatrix} \in \mathbb{R}^{N \times r}. \quad (9)$$

- a) Based on the model in Eqs. (7) and (8) and with known data as given in (9) we can develop the following matrix equations

$$Y_{J|L} = O_L X_J + H_L^d U_{J|L+g-1} + H_L^s E_{J|L}, \quad (10)$$

$$Y_{J+1|L} = \tilde{A}_L Y_{J|L} + \tilde{B}_L U_{J|L+g} + \tilde{C}_L E_{J|L+1}, \quad (11)$$

where  $J \geq 1$  and  $L \geq 1$  are user specified positive integer numbers.

Write down the structure of the matrices in the matrix Eqs. (10) and (11), with parameters  $N = 9$ ,  $L = 2$ ,  $J = 2$  and  $g = 0$ .

- b) By using (9) and Eqs. (10) and (11) we may formulate the equations

$$Z_{J|L} = O_L X_J^a \quad (12)$$

and

$$Z_{J+1|L} = \tilde{A}_L Z_{J|L} \quad (13)$$

Find expressions for the data matrices  $Z_{J|L}$  and  $Z_{J+1|L}$  for the following two cases:

- a deterministic system, i.e., when  $e_k = 0$ .
- a general combined deterministic and stochastic system.

Remark: define the projections which is involved in the expressions for  $Z_{J+1|L}$  and  $Z_{J|L}$ .

- c) Show how
- the system order,  $n$
  - the extended observability matrix  $O_L$
  - the system matrices  $A$  and  $D$

can be estimated.

- d) Consider now the following Kalman filter on innovations form

$$x_{k+1} = Ax_k + Bu_k + K\varepsilon_k, \quad (14)$$

$$y_k = Dx_k + Eu_k + \varepsilon_k \quad (15)$$

What is the relationship between the Kalman filter on innovations form in Eqs. (14) and (15) and the innovations formulation in Eqs. (7) and (8)?

- e) Consider that the known input and output data as given in (9) are collected in closed loop, i.e., we assume that there is feedback in the known data.

From Eq. (8) with  $E = 0$ , or Eq. (10) with  $L = 1$  and  $g = 0$ , we may define the matrix Equation

$$Y_{J|1} = DX_{J|1} + FE_{J|1} \quad (16)$$

- Define the data matrices  $Y_{J|1}$ ,  $X_{J|1}$  and  $E_{J|1}$ .
- Consider the projection

$$\begin{aligned} Z_{J|1}^s &= FE_{J|1} = Y_{J|1} - Y_{J|1} / \begin{bmatrix} U_{0|J} \\ Y_{0|J} \end{bmatrix} \\ &= \begin{bmatrix} Fe_J & Fe_{J+1} & \dots & Fe_{N-1} \end{bmatrix} \\ &= \begin{bmatrix} \varepsilon_J & \varepsilon_{J+1} & \dots & \varepsilon_{N-1} \end{bmatrix} \end{aligned} \quad (17)$$

Explain how this projection can be used in order to develop a subspace identification algorithm for closed loop systems.

### Task 3 (10%): Prediction error methods

A Kalman filter on innovations form for a linear discrete time system is given by

$$\bar{x}_{k+1} = A\bar{x}_k + Bu_k + Ke_k, \quad (18)$$

$$y_k = D\bar{x}_k + e_k \quad (19)$$

where  $\bar{x}_k$  is the predicted state,  $\bar{x}_1$  is the initial predicted state,  $y_k \in \mathbb{R}^m$  is the measurement vector and  $e_k$  is the innovations process.

We will assume that the following input and output data are known

$$\left. \begin{array}{l} u_k \\ y_k \end{array} \right\} \forall k = 1, \dots, N \quad (20)$$

- a) Write down a Kalman filter on prediction form, i.e. the filter used to compute the predicted measurement,  $\bar{y}_k$ , of the measurement  $y_k$ .
- b)
  - What is a parameter vector,  $\theta$ ?
  - Give an example of the relationship between the parameter vector  $\theta$  and the prediction formulation of a Kalman filter for a single output and single input dynamic system in state space model form, as in Eqs. (18) and (19) with  $n = 3$  states.
  - How many parameters,  $p$ , is it in this parameter vector,  $\theta \in \mathbb{R}^p$  ?

### Task 4 (16%): Ordinary Least Squares method and recursive system identification

- a) Given a system

$$\begin{bmatrix} x_{k+1}^1 \\ x_{k+1}^2 \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -a_1 & -a_0 \end{bmatrix} \begin{bmatrix} x_k^1 \\ x_k^2 \end{bmatrix} + \begin{bmatrix} b_0 \\ b_1 \end{bmatrix} u_k + \begin{bmatrix} k_0 \\ k_1 \end{bmatrix} e_k \quad (21)$$

$$y_k = [1 \ 0] \begin{bmatrix} x_k^1 \\ x_k^2 \end{bmatrix} + e_k \quad (22)$$

For which values of the parameters  $k_0$  and  $k_1$  may the above model be written as an ARX model and hence as a linear regression model of the form

$$y_k = \varphi_k^T \theta_0 + e_k \quad (23)$$

- In particular, define the regression vector,  $\varphi_k$ , and the parameter vector,  $\theta_0$ .
- Also define the parameters  $k_0$  and  $k_1$  such that the model, Eqs. (21) and (22), can be written as the linear regression model Eq. (23).

b)

- Based on the regression model in Eq. (23) above, find a predictor,  $\bar{y}_k(\theta)$ , for the measurement  $y_k$ .
- Define the prediction error,  $\varepsilon_k$ .

c) Consider the following prediction error criterion

$$V_N(\theta) = \frac{1}{N} \sum_{k=1}^N \varepsilon_k^T \Lambda \varepsilon_k \quad (24)$$

where  $\Lambda$  is a specified and symmetric weighting matrix.

Find the Ordinary Least Squares (OLS) estimate,  $\hat{\theta}_N$ , of the true parameter vector  $\theta_0$ .

d) The mean of a variable,  $y_k$ , for  $k = 1, 2, \dots, t$  where  $t$  is present discrete time, is given by

$$\bar{y}_t = \frac{1}{t} \sum_{k=1}^t y_k. \quad (25)$$

Develop a recursive algorithm for computing the mean  $\bar{y}_t$  ?

e) Based on the OLS solution in step c) above, show how we can develop a recursive Ordinary Least Squares (ROLS) method of the following form

$$\hat{\theta}_t = \hat{\theta}_{t-1} + K_t(y_t - \varphi_t^T \hat{\theta}_{t-1}) \quad (26)$$

You shall in particular find equations for computing the gain,  $K_t$ , in Equation (26).

## Task 5 (12%): Realization theory and the Kalman filter

a) Assume known impulse responses

$$H_k = DA^{k-1}B \quad \forall k = 1, \dots, 7. \quad (27)$$

Answer the following:

- Write up the Hankel matrices  $\mathbf{H}_{1|L}$  and  $\mathbf{H}_{2|L}$  where you should use  $L = 2$ .
  - Show how you can find the system order,  $n$ , the extended observability matrix  $O_L$  and the extended controllability matrix  $C_J$  from a Singular Value decomposition (SVD) of  $\mathbf{H}_{1|L}$ .
  - How are  $\mathbf{H}_{1|L}$  and  $\mathbf{H}_{2|L}$  related to  $O_L$  and  $C_J$ ?
- b) Given a system modelled by a discrete time, state space model as follows

$$x_{k+1} = Ax_k + Bu_k + v_k, \quad (28)$$

$$y_k = Dx_k + Eu_k + w_k, \quad (29)$$

where  $v_k$  is white process noise and  $w_k$  is white measurements noise. Assume that the noise are uncorrelated, i.e.  $E(v_k w_k^T) = 0$ .

- Write down a Kalman filter on apriori-aposteriori form for optimal estimation of the state vector  $x_k$ .
  - Find a formula for the Kalman filter gain matrix,  $K$ , in the Kalman filter on apriori-aposteriori form.
  - Show how the apriori-aposteriori formulation of the Kalman filter can be written as a Kalman filter on innovations form.
- c) Given a non-linear system

$$x_{k+1} = f(x_k, u_k) + v_k \quad (30)$$

$$y_k = g(x_k) + w_k \quad (31)$$

where  $v_k$  and  $w_k$  are discrete white process noise and discrete white measurements noise, respectively.

Formulate the Kalman filter on apriori-aposteriori form for the non-linear system model in Eqs. (30) and (31).

d) Why is a Kalman-filter often called an optimal estimator?